

FEATURES

Very low voltage noise: 1.8 nV/ $\sqrt{\text{Hz}}$
Low input bias current: 90 nA maximum
Offset voltage: 125 μV maximum
High gain: 120 dB
Wide bandwidth: 12 MHz
 $\pm 5\text{ V}$ to $\pm 15\text{ V}$ operation

APPLICATIONS

Precision instrumentation
Filter blocks
Microphone preamplifiers
Industrial control
Thermocouples and RTDs
Reference buffers

GENERAL DESCRIPTION

The ADA4004-1/ADA4004-2/ADA4004-4 are 1.8 nV/ $\sqrt{\text{Hz}}$ precision amplifiers featuring 40 μV offset, 0.7 $\mu\text{V}/^\circ\text{C}$ drift, 12 MHz bandwidth, and low 1.7 mA per amplifier supply current.

The ADA4004-1/ADA4004-2/ADA4004-4 are designed on the high performance *iPolar*[™] process, enabling improvements such as reduced noise and power consumption, increased speed and stability, and smaller footprint size. Novel design techniques enable the ADA4004-1/ADA4004-2/ADA4004-4 to achieve 1.8 nV/ $\sqrt{\text{Hz}}$ voltage noise density and a low 6 Hz 1/f noise corner frequency while consuming just 1.7 mA per amplifier. The small package saves board space, reduces cost, and improves layout flexibility.

Applications for these amplifiers include high precision controls, PLL filters, high performance precision filters, medical and analytical instrumentation, precision power supply controls, ATE, and data acquisition systems. Operation is fully specified from $\pm 5\text{ V}$ to $\pm 15\text{ V}$ from -40°C to $+125^\circ\text{C}$.

The ADA4004-1, ADA4004-2, and ADA4004-4 are members of a growing series of low noise op amps offered by Analog Devices, Inc., (see Table 1).

Table 1. Voltage Noise

| Pkg. | 0.9 nV | 1.1 nV | 1.8 nV | 2.8 nV | 3.8 nV |
|--------|--------|--------|-----------|--------|--------|
| Single | AD797 | AD8597 | ADA4004-1 | AD8675 | AD8671 |
| Dual | | AD8599 | ADA4004-2 | AD8676 | AD8672 |
| Quad | | | ADA4004-4 | | AD8674 |

PIN CONFIGURATIONS




Figure 1. 5-Lead SOT (RJ-5)




Figure 2. 8-Lead SOIC (R-8)




Figure 3. 8-Lead MSOP (RM-8) and 8-Lead SOIC (R-8)





Figure 4. 14-Lead SOIC (R-14)



NOTES
 1. NC = NO CONNECT.
 2. IT IS RECOMMENDED THAT THE EXPOSED PAD BE CONNECTED TO V-.

Figure 5. 16-Lead LFCSP (CP-16-23)

TABLE OF CONTENTS

Features 1
 Applications..... 1
 General Description 1
 Pin Configurations 1
 Revision History 2
 Specifications..... 3

Absolute Maximum Ratings5
 Thermal Resistance5
 ESD Caution.....5
 Typical Performance Characteristics6
 Outline Dimensions 12
 Ordering Guide 14

REVISION HISTORY

7/15—Rev. G to Rev. H

Changed CP-16-4 to CP-16-23 and Changed LFCSP_VQ to LFCSP_WQ Throughout
 Changes to Figure 5..... 1
 Changed Differential Input Voltage Parameter, Table 4..... 5
 Updated Outline Dimensions 12
 Changes to Ordering Guide 15

4/11—Rev. F to Rev. G

Changes to Figure 1 1
 Updated Outline Dimensions 12

6/10—Rev. E to Rev. F

Added Differential Input Current to Table 4 5
 Changes to Figure 14 and Figure 17 7

10/09—Rev. D to Rev. E

Changes to Product Title, General Description Section, and Figure 5 1
 Updated Outline Dimensions (RM-8)..... 13
 Changes to Ordering Guide 14

6/09—Rev. C to Rev. D

Changes to Figure 5..... 1

10/08—Rev. B to Rev. C

Added ADA4004-1 and ADA4004-2 Universal
 Added 5-Lead SOT, 8-Lead SOIC, and 8-Lead MSOP Universal
 Changes to Features Section 1
 Added Figure 1 to Figure 3; Renumbered Sequentially..... 1
 Changes to General Description Section 1

Added Table 1; Renumbered Sequentially 1
 Change to Output Voltage Low Parameter, Table 2..... 3
 Changes to Supply Current per Amplifier Parameter, Table 2 3
 Added Phase Margin Parameter, Table 2..... 3
 Change to Output Voltage Low Parameter, Table 3..... 3
 Changes to Supply Current per Amplifier Parameter, Table 3 4
 Added Phase Margin Parameter, Table 3..... 4
 Changes to Table 4 5
 Changes to Thermal Resistance Section..... 5
 Changes to Table 5 5
 Update Outline Dimensions..... 12
 Changes to Ordering Guide..... 13

11/07—Rev. A to Rev. B

Changed V_S to V_{SY} Universal
 Changes to General Description 1
 Changes to Supply Current per Amplifier 3
 Changes to Open-Loop Gain 4
 Changes to Supply Current per Amplifier 4
 Changes to Figure 10, Figure 11, Figure 13, and Figure 14..... 7
 Changes to Figure 26..... 9
 Updated Outline Dimensions 12
 Changes to Ordering Guide 12

7/06—Rev. 0 to Rev. A

Changes to Table 4..... 5
 Updated Outline Dimensions 12
 Changes to Ordering Guide 12

1/06—Revision 0: Initial Version

SPECIFICATIONS

$V_{SY} = \pm 5\text{ V}$, $V_{CM} = 0\text{ V}$, $T_A = 25^\circ\text{C}$, unless otherwise specified.

Table 2.

| Parameter | Symbol | Conditions | Min | Typ | Max | Unit |
|-------------------------------|--------------------------|---|------|----------|-------|------------------------------|
| INPUT CHARACTERISTICS | | | | | | |
| Offset Voltage | V_{OS} | $-40^\circ\text{C} \leq T_A \leq +125^\circ\text{C}$ | | 40 | 140 | μV |
| | | | | | | 300 |
| Input Bias Current | I_B | $-40^\circ\text{C} \leq T_A \leq +125^\circ\text{C}$ | | 40 | 85 | nA |
| | | | | | | 165 |
| Input Offset Current | I_{OS} | $-40^\circ\text{C} \leq T_A \leq +125^\circ\text{C}$ | | 40 | 85 | nA |
| | | | | | | 100 |
| Input Voltage Range | IVR | | -3.5 | | +3.5 | V |
| Common-Mode Rejection Ratio | CMRR | $V_{CM} = -3.0\text{ V to }+3.0\text{ V}$ $-40^\circ\text{C} \leq T_A \leq +125^\circ\text{C}$ | | 105 | 111 | dB |
| | | | | 95 | 110 | dB |
| Open-Loop Gain | A_{VO} | $R_L = 2\text{ k}\Omega$, $V_{OUT} = -2.5\text{ V to }+2.5\text{ V}$ $-40^\circ\text{C} \leq T_A \leq +125^\circ\text{C}$ | | 250 | 400 | V/mV |
| | | | | 170 | | V/mV |
| Offset Voltage Drift | $\Delta V_{OS}/\Delta T$ | $-40^\circ\text{C} \leq T_A \leq +125^\circ\text{C}$ | | 0.7 | 1 | $\mu\text{V}/^\circ\text{C}$ |
| OUTPUT CHARACTERISTICS | | | | | | |
| Output Voltage High | V_{OH} | $R_L = 2\text{ k}\Omega$ to ground $-40^\circ\text{C} \leq T_A \leq +125^\circ\text{C}$ | | 3.7 | 3.9 | V |
| | | | | 3.4 | 3.6 | V |
| Output Voltage Low | V_{OL} | $R_L = 2\text{ k}\Omega$ to ground $-40^\circ\text{C} \leq T_A \leq +125^\circ\text{C}$ | | -3.6 | -3.55 | V |
| | | | | -3.6 | -3.4 | V |
| Short-Circuit Limit | I_{SC} | $-40^\circ\text{C} \leq T_A \leq +125^\circ\text{C}$ | | 25 | | mA |
| | | | | | | |
| Output Current | I_O | $V_{OUT} = \pm 3.6\text{ V}$ | | ± 10 | | mA |
| POWER SUPPLY | | | | | | |
| Power Supply Rejection Ratio | PSRR | $V_{SY} = \pm 5\text{ V to } \pm 15\text{ V}$ $-40^\circ\text{C} \leq T_A \leq +125^\circ\text{C}$ | | 110 | 118 | dB |
| | | | | 110 | | dB |
| Supply Current per Amplifier | I_{SY} | $-40^\circ\text{C} \leq T_A \leq +125^\circ\text{C}$ | | | 2.0 | mA |
| | | | | | 2.2 | mA |
| DYNAMIC PERFORMANCE | | | | | | |
| Slew Rate | SR | $R_L = 2\text{ k}\Omega$ to ground | | 2.7 | | V/ μs |
| Gain Bandwidth Product | GBP | | | 12 | | MHz |
| Phase Margin | Φ_M | | | 48 | | Degrees |
| NOISE PERFORMANCE | | | | | | |
| Voltage Noise | $e_{n\text{ p-p}}$ | $f = 0.1\text{ Hz to }10\text{ Hz}$ | | 0.1 | | $\mu\text{V p-p}$ |
| Voltage Noise Density | e_n | $f = 1\text{ kHz}$ | | 1.8 | | nV/ $\sqrt{\text{Hz}}$ |
| Current Noise Density | i_n | $f = 10\text{ Hz}$ | | 3.5 | | pA/ $\sqrt{\text{Hz}}$ |
| Current Noise Density | i_n | $f = 200\text{ Hz}$ | | 1.2 | | pA/ $\sqrt{\text{Hz}}$ |

$V_{SY} = \pm 15\text{ V}$, $V_{CM} = 0\text{ V}$, $T_A = 25^\circ\text{C}$, unless otherwise specified.

Table 3.

| Parameter | Symbol | Conditions | Min | Typ | Max | Unit |
|-------------------------------|--------------------------|--|-------|----------|-------|------------------------------|
| INPUT CHARACTERISTICS | | | | | | |
| Offset Voltage | V_{OS} | $-40^\circ\text{C} \leq T_A \leq +125^\circ\text{C}$ | | 40 | 125 | μV |
| Input Bias Current | I_B | $-40^\circ\text{C} \leq T_A \leq +125^\circ\text{C}$ | | 40 | 270 | μV |
| Input Offset Current | I_{OS} | $-40^\circ\text{C} \leq T_A \leq +125^\circ\text{C}$ | | | 90 | nA |
| Input Voltage Range | IVR | $-40^\circ\text{C} \leq T_A \leq +125^\circ\text{C}$ | | | 165 | nA |
| Common-Mode Rejection Ratio | CMRR | $V_{CM} = -12.5\text{ V to } +12.5\text{ V}$ $-40^\circ\text{C} \leq T_A \leq +125^\circ\text{C}$ | -12.5 | 113 | +12.5 | V |
| Open-Loop Gain | A_{VO} | $R_L = 2\text{ k}\Omega$, $V_{OUT} = -12.0\text{ V to } +12.0\text{ V}$ $-40^\circ\text{C} \leq T_A \leq +125^\circ\text{C}$ | 110 | 104 | | dB |
| Offset Voltage Drift | $\Delta V_{OS}/\Delta T$ | $-40^\circ\text{C} \leq T_A \leq +125^\circ\text{C}$ | 250 | 500 | | dB |
| OUTPUT CHARACTERISTICS | | | | | | |
| Output Voltage High | V_{OH} | $R_L = 2\text{ k}\Omega$ to ground $-40^\circ\text{C} \leq T_A \leq +125^\circ\text{C}$ | 13.4 | 13.6 | | V |
| Output Voltage Low | V_{OL} | $R_L = 2\text{ k}\Omega$ to ground $-40^\circ\text{C} \leq T_A \leq +125^\circ\text{C}$ | 13.1 | 13.3 | | V |
| Short-Circuit Limit | I_{SC} | | | 25 | | mA |
| Output Current | I_O | $V_{OUT} = \pm 13.6\text{ V}$ | | ± 10 | | mA |
| POWER SUPPLY | | | | | | |
| Power Supply Rejection Ratio | PSRR | $V_{SY} = \pm 5\text{ V to } \pm 15\text{ V}$ $-40^\circ\text{C} \leq T_A \leq +125^\circ\text{C}$ | 110 | 118 | | dB |
| Supply Current per Amplifier | I_{SY} | $-40^\circ\text{C} \leq T_A \leq +125^\circ\text{C}$ | 110 | | 2.2 | dB |
| DYNAMIC PERFORMANCE | | | | | | |
| Slew Rate | SR | $R_L = 2\text{ k}\Omega$ to ground | | 2.7 | | $\text{V}/\mu\text{s}$ |
| Gain Bandwidth Product | GBP | | | 12 | | MHz |
| Phase Margin | Φ_M | | | 48 | | Degrees |
| NOISE PERFORMANCE | | | | | | |
| Voltage Noise | $e_{n,p-p}$ | $f = 0.1\text{ Hz to } 10\text{ Hz}$ | | 0.15 | | $\mu\text{V p-p}$ |
| Voltage Noise Density | e_n | $f = 1\text{ kHz}$ | | 1.8 | | $\text{nV}/\sqrt{\text{Hz}}$ |
| Current Noise Density | i_n | $f = 10\text{ Hz}$ | | 3.5 | | $\text{pA}/\sqrt{\text{Hz}}$ |
| Current Noise Density | i_n | $f = 200\text{ Hz}$ | | 1.2 | | $\text{pA}/\sqrt{\text{Hz}}$ |

ABSOLUTE MAXIMUM RATINGS

Table 4.

| Parameter | Rating |
|--------------------------------------|---|
| Supply Voltage | $\pm 18\text{ V}$ or $+36\text{ V}$ |
| Input Voltage | $V_- < V_{IN} < V_+$ |
| Differential Input Voltage | $\pm 600\text{ mV}$ |
| Differential Input Current | $\pm 5\text{ mA}$ |
| Output Short-Circuit Duration to GND | Indefinite |
| Storage Temperature Range | -65°C to $+150^\circ\text{C}$ |
| Operating Temperature Range | -40°C to $+125^\circ\text{C}$ |
| Junction Temperature Range | -65°C to $+150^\circ\text{C}$ |
| Lead Temperature (Soldering 60 sec) | 300°C |

Stresses at or above those listed under Absolute Maximum Ratings may cause permanent damage to the product. This is a stress rating only; functional operation of the product at these or any other conditions above those indicated in the operational section of this specification is not implied. Operation beyond the maximum operating conditions for extended periods may affect product reliability.

THERMAL RESISTANCE

θ_{JA} is specified with the device soldered on a circuit board with its exposed paddle soldered to a pad (if applicable) on a 4-layer JEDEC standard printed circuit board with zero airflow.

Table 5.

| Package Type | θ_{JA} | θ_{JC} | Unit |
|--|---------------|---------------|---------------------------|
| 5-Lead SOT (RJ-5) | 230 | 92 | $^\circ\text{C}/\text{W}$ |
| 8-Lead SOIC (R-8), ADA4004-1 | 177 | 53 | $^\circ\text{C}/\text{W}$ |
| 8-Lead SOIC (R-8), ADA4004-2 | 155 | 45 | $^\circ\text{C}/\text{W}$ |
| 8-Lead MSOP (RM-8) | 186 | 52 | $^\circ\text{C}/\text{W}$ |
| 14-Lead SOIC_N (R-14) | 115 | 36 | $^\circ\text{C}/\text{W}$ |
| 16-Lead LFCSP_VQ (CP-16-4) | 44 | 31.5 | $^\circ\text{C}/\text{W}$ |

ESD CAUTION



ESD (electrostatic discharge) sensitive device. Charged devices and circuit boards can discharge without detection. Although this product features patented or proprietary protection circuitry, damage may occur on devices subjected to high energy ESD. Therefore, proper ESD precautions should be taken to avoid performance degradation or loss of functionality.

TYPICAL PERFORMANCE CHARACTERISTICS




Figure 6. Number of Amplifiers vs. Input Offset Voltage




Figure 9. Number of Amplifiers vs. TCV_{os}




Figure 7. Number of Amplifiers vs. Input Offset Voltage




Figure 10. Number of Amplifiers vs. TCV_{os}




Figure 8. Input Offset Voltage vs. Temperature




Figure 11. Input Bias Current vs. Temperature




Figure 12. Supply Current vs. Total Supply Voltage




Figure 15. Supply Current vs. Temperature




Figure 13. V_{OH} vs. Temperature




Figure 16. V_{OL} vs. Temperature




Figure 14. Open-Loop Gain and Phase vs. Frequency




Figure 17. Open-Loop Gain and Phase vs. Frequency




Figure 18. Open-Loop Gain vs. Temperature

06577-018




Figure 21. Closed-Loop Gain vs. Frequency

06577-021




Figure 19. Closed-Loop Gain vs. Frequency

06577-019




Figure 22. Output Impedance vs. Frequency

06577-022




Figure 20. Output Impedance vs. Frequency

06577-020




Figure 23. PSRR vs. Frequency

06577-023




Figure 24. PSRR vs. Temperature

05577-024




Figure 27. CMRR vs. Frequency

05577-027




Figure 25. CMRR vs. Temperature

05577-025




Figure 28. Output Voltage vs. Current Load

05577-028




Figure 26. Output Voltage vs. Current Load

05577-026




Figure 29. Small-Signal Overshoot vs. Capacitive Load

05577-029




Figure 30. Small-Signal Overshoot vs. Capacitive Load




Figure 33. Large-Signal Transient Response




Figure 31. Small-Signal Transient Response




Figure 34. Small-Signal Transient Response




Figure 32. No Phase Reversal




Figure 35. Voltage Noise (0.1 Hz to 10 Hz)




Figure 36. Voltage Noise (0.1 Hz to 10 Hz)




Figure 38. Current Noise Density vs. Frequency




Figure 37. Voltage Noise Density vs. Frequency





Figure 39. Channel Separation vs. Frequency


OUTLINE DIMENSIONS



COMPLIANT TO JEDEC STANDARDS MO-178-AA

Figure 40. 5-Lead Small Outline Transistor Package [SOT-23] (RJ-5)
Dimensions shown in millimeters

11-01-2010-A



COMPLIANT TO JEDEC STANDARDS MS-012-AA
CONTROLLING DIMENSIONS ARE IN MILLIMETERS; INCH DIMENSIONS (IN PARENTHESES) ARE ROUNDED-OFF MILLIMETER EQUIVALENTS FOR REFERENCE ONLY AND ARE NOT APPROPRIATE FOR USE IN DESIGN.

Figure 41. 8-Lead Standard Small Outline Package [SOIC_N] Narrow Body (R-8)
Dimensions shown in millimeters and (inches)

012607-A

ORDERING GUIDE

| Model ¹ | Temperature Range | Package Description | Package Option | Branding |
|--------------------|-------------------|---------------------|----------------|----------|
| ADA4004-1ARJZ-R2 | -40°C to +125°C | 5-Lead SOT-23 | RJ-5 | A1M |
| ADA4004-1ARJZ-R7 | -40°C to +125°C | 5-Lead SOT-23 | RJ-5 | A1M |
| ADA4004-1ARJZ-RL | -40°C to +125°C | 5-Lead SOT-23 | RJ-5 | A1M |
| ADA4004-1ARZ | -40°C to +125°C | 8-Lead SOIC_N | R-8 | |
| ADA4004-1ARZ-R7 | -40°C to +125°C | 8-Lead SOIC_N | R-8 | |
| ADA4004-1ARZ-RL | -40°C to +125°C | 8-Lead SOIC_N | R-8 | |
| ADA4004-2ARMZ | -40°C to +125°C | 8-Lead MSOP | RM-8 | A1N |
| ADA4004-2ARMZ-RL | -40°C to +125°C | 8-Lead MSOP | RM-8 | A1N |
| ADA4004-2ARMZ-R7 | -40°C to +125°C | 8-Lead MSOP | RM-8 | A1N |
| ADA4004-2ARZ | -40°C to +125°C | 8-Lead SOIC_N | R-8 | |
| ADA4004-2ARZ-RL | -40°C to +125°C | 8-Lead SOIC_N | R-8 | |
| ADA4004-2ARZ-R7 | -40°C to +125°C | 8-Lead SOIC_N | R-8 | |
| ADA4004-4ACPZ-R2 | -40°C to +125°C | 16-Lead LFCSP_WQ | CP-16-23 | |
| ADA4004-4ACPZ-R7 | -40°C to +125°C | 16-Lead LFCSP_WQ | CP-16-23 | |
| ADA4004-4ACPZ-RL | -40°C to +125°C | 16-Lead LFCSP_WQ | CP-16-23 | |
| ADA4004-4ARZ | -40°C to +125°C | 14-Lead SOIC_N | R-14 | |
| ADA4004-4ARZ-R7 | -40°C to +125°C | 14-Lead SOIC_N | R-14 | |
| ADA4004-4ARZ-RL | -40°C to +125°C | 14-Lead SOIC_N | R-14 | |

¹ Z = RoHS Compliant Part.

NOTES

NOTES

Mouser Electronics

Authorized Distributor

Click to View Pricing, Inventory, Delivery & Lifecycle Information:

[Analog Devices Inc.:](#)

[ADA4004-2ARMZ](#) [ADA4004-2ARZ](#) [ADA4004-4ARZ](#) [ADA4004-1ARJZ-R7](#) [ADA4004-1ARZ](#) [ADA4004-1ARZ-R7](#)
[ADA4004-2ARMZ-R7](#) [ADA4004-2ARMZ-RL](#) [ADA4004-2ARZ-R7](#) [ADA4004-2ARZ-RL](#) [ADA4004-4ACPZ-R7](#)
[ADA4004-4ACPZ-RL](#) [ADA4004-4ARZ-R7](#) [ADA4004-4ARZ-RL](#)